OPTONICA

DATASHEET

NOARK

# Residual Current Circuit Breaker Ex9L-N 4P 40A A 100mA

**Stamps**

CE RoHS

## Especificación técnica

| | | | |
|---|---|---|---|
| **Brand** | NOARK | **Rated fault current [A]** | 0.1 |
| **IP** | 20 | **Leakage current type** | A |
| **EAN Code** | 8592765083661 | **Selective protection** | No |
| **Operating Frequency** | 50Hz | **Short-circuit breaking capacity (Icw) [kA]** | 6 |
| **Mounting method** | DIN rail | **Surge current capacity [kA]** | 3 |
| **Width in number of modular spacings** | 4 | **Additional equipment possible** | No |
| **Power loss [W]** | 15.3 | **Construction size (in accordance with DIN 43880)** | 4 |
| **Number of poles (total)** | 4 | **Built-in depth [mm]** | 79 |
| **Nominal rated voltage [V]** | 400 | **Short-time delayed tripping** | No |
| **Nominal rated current [A]** | 40 | **Warranty** | 5 Years |