

# OPTONICA

**NOARK**



## Residual Current Circuit Breaker Ex9L-N 2P 40A A 100mA

### Stamps



## Technical Specification

<b>Catalog Number</b>	108354
<b>Brand</b>	NOARK
<b>IP</b>	20
<b>EAN Code</b>	8592765083548
<b>Operating Frequency</b>	50Hz

<b>Body Color</b>	White
<b>Mounting method</b>	DIN rail
<b>Width in number of modular spacings</b>	2
<b>Power loss [W]</b>	7.2
<b>Number of poles (total)</b>	2
<b>Nominal rated voltage [V]</b>	230
<b>Nominal rated current [A]</b>	40
<b>Rated fault current [A]</b>	0.1
<b>Leakage current type</b>	A
<b>Selective protection</b>	No
<b>Short-circuit breaking capacity (I<sub>cn</sub>) [kA]</b>	6
<b>Surge current capacity [kA]</b>	3
<b>Additional equipment possible</b>	No
<b>Construction size (in accordance with DIN 43880)</b>	2
<b>Built-in depth [mm]</b>	79
<b>Short-time delayed tripping</b>	No
<b>Warranty</b>	5 Years