

**NOARK**



### Miniature Circuit Breaker Ex9BN 3P C6

Stamps



## Техническа Спецификация

|  |               |  |         |
|--|---------------|--|---------|
| <b>Brand</b>                               | NOARK         | <b>Built-in depth [mm]</b>   | 74      |
| <b>Product Code</b>                        | Ex9BN 3P C6   | <b>Concurrently switching N-neutral</b>                                    | No      |
| <b>IP</b>                                  | 20            | <b>Release characteristic</b>  | C       |
| <b>EAN Code</b>                            | 8592765001405 | <b>Number of protected poles</b>   | 3       |
| <b>Frequency</b>                           | 50/60Hz       | <b>Rated short-circuit breaking capacity Icn EN 60898 at 230 V [kA]</b>    | 6       |
| <b>Width in number of modular spacings</b> | 3             | <b>Rated short-circuit breaking capacity Icu IEC 60947-2 at 230 V [kA]</b> | 10      |
| <b>Power loss [W]</b>                      | 7.5           | <b>Voltage type</b>  | AC      |
| <b>Number of poles (total)</b>             | 3             | <b>Current limiting class</b>  | 3       |
| <b>Nominal rated voltage [V]</b>           | 400           | <b>Over voltage category</b>   | 3       |
| <b>Nominal rated current [A]</b>           | 6             | <b>Pollution degree</b>  | 2       |
| <b>Additional equipment possible</b>       | Yes           | <b>Warranty</b>  | 5 Years |