

# OPTONICA

**NOARK**



## Miniature Circuit Breaker Ex9BN 1P C32

### Stamps



## Technical Specification

<b>Catalog Number</b>	100101
<b>Brand</b>	NOARK
<b>IP</b>	20
<b>EAN Code</b>	8592765001023
<b>Operating Frequency</b>	50-60 Hz
<b>Width in number of modular spacings</b>	1

<b>Power loss [W]</b>	3.8
<b>Number of poles (total)</b>	1
<b>Nominal rated voltage [V]</b>	230
<b>Nominal rated current [A]</b>	32
<b>Additional equipment possible</b>	Yes
<b>Built-in depth [mm]</b>	72
<b>Concurrently switching N-neutral</b>	No
<b>Release characteristic</b>	C
<b>Number of protected poles</b>	1
<b>Rated short-circuit breaking capacity I<sub>cn</sub> EN 60898 at 230 V [kA]</b>	6
<b>Rated short-circuit breaking capacity I<sub>cu</sub> IEC 60947-2 at 230 V [kA]</b>	10
<b>Voltage type</b>	AC
<b>Current limiting class</b>	3
<b>Over voltage category</b>	3
<b>Pollution degree</b>	2
<b>Warranty</b>	5 Years