

NOARK



### Residual Current Circuit Breaker Ex9L-N 2P 63A 30mA

Stamps

CE

RoHS



## Техническа Спецификация

<b>Brand</b>	NOARK	<b>Rated fault current [A]</b>	0.03
<b>Product Code</b>	Ex9L-N 2P 63A AC 30mA 6kA EU	<b>Leakage current type</b>	AC
<b>IP</b>	20	<b>Selective protection</b>	No
<b>EAN Code</b>	8592765083166	<b>Short-circuit breaking capacity (I<sub>cn</sub>) [kA]</b>	6
<b>Frequency</b>	50/60Hz	<b>Surge current capacity [kA]</b>	3
<b>Mounting method</b>	DIN rail	<b>Additional equipment possible</b>	No
<b>Width in number of modular spacings</b>	2	<b>Construction size (in accordance with DIN 43880)</b>	2
<b>Power loss [W]</b>	15	<b>Built-in depth [mm]</b>	79
<b>Number of poles (total)</b>	2	<b>Short-time delayed tripping</b>	No
<b>Nominal rated voltage [V]</b>	230	<b>Warranty</b>	5 Years
<b>Nominal rated current [A]</b>	63		