


### Alimentatore Per Fari Magnetici Larghezza M35



#### Potenza

6W

#### Colore della luce

 Luce fredda

#### Stamps



## Specifiche tecniche

<b>Brand</b>	Optonica	<b>On/Off Cycles</b>	100 000x
<b>Product Code</b>	DL6-B1	<b>Instant On</b>	0.2s
<b>Power</b>	6W	<b>Operating Frequency</b>	50-60 Hz
<b>Energy Consumption</b>	6 kWh/1000h	<b>Temperature</b>	-20°C / +40°C
<b>Input voltage</b>	AC85-265V	<b>Ra ≥</b>	80
<b>Flux</b>	480 lm	<b>Life span</b>	25 000 Hours
<b>FLUX per watt</b>	80 lm/W	<b>Color Code</b>	860
<b>IP</b>	20	<b>Lumen maintenance at end of service life</b>	70%
<b>Dimmable</b>	No	<b>Size of product</b>	φ120 x 38 mm
<b>Correlated Color Temperature</b>	6000K	<b>Size of package</b>	130x125x40 mm
<b>Light Color</b>	Luce fredda	<b>Size of Box</b>	420x270x285 mm
<b>Wattage Equivalent</b>	48W	<b>Items per pack</b>	1
<b>EAN Code</b>	3800156624016	<b>Items per box</b>	40
<b>Energy Efficiency Label</b>	F	<b>Material</b>	Aluminium
<b>Beam angle</b>	120°	<b>Gross weight</b>	0,130 kg
<b>Power Factor</b>	0.5	<b>Net weight</b>	0,101 kg
<b>Power LED</b>	6W	<b>Warranty</b>	2 Years