

**NOARK**



### Residual Current Circuit Breaker Ex9L-N 4P 63A 100mA

Stamps



RoHS



## Specifiche tecniche

|                                     |               |                                                         |         |
|-------------------------------------|---------------|---------------------------------------------------------|---------|
| Brand                               | NOARK         | Rated fault current [A]                                 | 0.1     |
| IP                                  | 20            | Leakage current type                                    | AC      |
| EAN Code                            | 8592765083371 | Selective protection                                    | No      |
| Operating Frequency                 | 50Hz          | Short-circuit breaking capacity (I <sub>cn</sub> ) [kA] | 6       |
| Mounting method                     | DIN rail      | Surge current capacity [kA]                             | 3       |
| Width in number of modular spacings | 4             | Additional equipment possible                           | No      |
| Power loss [W]                      | 24            | Construction size (in accordance with DIN 43880)        | 4       |
| Number of poles (total)             | 4             | Built-in depth [mm]                                     | 79      |
| Nominal rated voltage [V]           | 400           | Short-time delayed tripping                             | No      |
| Nominal rated current [A]           | 63            | Warranty                                                | 5 Years |